




Dell Inspiron 15 3567 Memory Module Replacement


Written By: Teren Wallace



INTRODUCTION

In this guide, we will be show how to remove and replace the Memory Module.


Step 1 — Popping up the Memory Module



⚠ WARNING: Before working inside your computer, read the safety information that shipped with your computer and follow the steps in [Before Working Inside Your Computer](#). After working inside your computer, follow the instructions in [After Working Inside Your Computer](#).


- Using your fingertips, carefully spread apart the securing clips on each end of the memory-module slot until the memory module pops up.

Step 2 — Sliding the Memory Module




- Slide and remove the memory module from the memory-module slot

Step 3 — Align the Notch



- Align the notch on the **NEW** memory module with the tab on the memory-module slot and slide it firmly into the slot at an angle.

Step 4 — Installing the Memory Module



- Press the memory module down until it clicks into place.
- ⓘ NOTE: If you do not hear the click, remove the memory module and reinstall it.